

GRAITEC ADVANCE

Advance Design

Installation troubleshooting guide



Content

ERROR CODE PROBLEMS	3
Error code 301: Unknown protection system. Verify the installation.	3
Error code 302: The software cannot be used. The computer date and time are older than the last time the software was used	4
Error code 313: The software cannot be used. The computer date and time are not up to date.....	4
Error code 303: The expiry date of your temporary license is near. Contact customer support.	4
Error code 304: The software version is not available for the protection system.....	5
Error code 307: The protection system has not been initialized.....	5
Error code 308: The protection system has been altered.....	5
Error code 309: The codes sent by the key are not the right ones. Verify the protection system installation.....	6
Error code 400: Protection type is not defined at the general environment level.....	6
Error code 451: To use the software on the protection server it is necessary to select the 'NETHASP' protection type	6
Error code 500: The license code does not have 21 characters	7
Error code 501: Invalid license code.....	7
APPENDIX	8

Error code problems

Error code 301: *Unknown protection system. Verify the installation.*

Displayed message Le système de protection n'est pas reconnu. Vérifiez son installation.

Cause 1 The HASP dongle is not attached on the USB or LPT port.

Solution

Plug the HASP dongle into the USB or LPT port of the computer.

Cause 2 The HASP dongle is attached, but the port drop-down list from the “Protection” application is pointing to a different location.

Solution

In case only one USB dongle is used, make sure it is an **Advance Design / OMD** formatted dongle (Advance Steel and Advance Concrete USB dongles look similar, but the HASP memory has a different format).

- If the **Advance Design / OMD** dongle is plugged in, in the “Protection” application, check if the port is set to **Auto**.
- If the installed version is **AD3.1 Base** or **SP1** delete the following key from the registry: “HKEY_LOCAL_MACHINE\SOFTWARE\Graitec\Advance Design 3.1\ LockPort”.

Note: *If the installed version is **AD 3.1 SP2** or a more recent one, ignore this solution as the problem is already fixed in the code.*

Cause 3 The communication between the “Protection” application and the HASP dongle is blocked by a firewall or antivirus software.

Solution

If the Windows firewall is activated, try to install the latest HASP drivers: **HASPUserSetup.exe**. This tool automatically adds new entries in the “Exceptions” list of the Windows Firewall.

- If another firewall is activated (antivirus software) instead of the Windows native firewall, check if the UDP ports 1947 or 475 are open.
- Use the **DiagnostiX** tool from the Aladdin Knowledge Systems Ltd. to test the communication between the HASP dongle and the operating system.

Error code 302: *The software cannot be used. The computer date and time are older than the last time the software was used.*

Displayed message L'utilisation du programme n'est pas possible, car la date et l'heure de l'ordinateur sont inférieures à celles de la dernière utilisation du logiciel.

Cause The HASP dongle is time protected (i.e. there is a date when the license expires) and the computer time is before the application time.

Solutions

1. When using **Advance Design / OMD**, the protection component is writing the computer time (CT) on the dongle HASP memory (date, time hh:mm:ss). This is named "application time" (AT), i.e. the date the software was last used.
 - The protection compares the computer time and the application time and raises the error if $CT < AT$;
 - The error can be avoided if the computers (where the dongle is used) are synchronized with the real time: the time has to be checked before using **Advance Design / OMD**.
2. A possible solution when $CT < AT$ is only when AT is the real time: add the computer time (CT) to the real time

Error code 313: *The software cannot be used. The computer date and time are not up to date.*

Displayed message L'utilisation du programme n'est pas possible, car la date et l'heure de l'ordinateur ne sont pas à jour.

Cause The HASP dongle is time protected (i.e. there is a date when the license expires) and the computer date is older than the dongle activation date.

Solution

Check the computer time and set it to the real time.

Error code 303: *The expiry date of your temporary license is near. Contact customer support.*

Displayed message La date de validité de votre code d'utilisation provisoire arrive à son terme. Effectuez sans tarder votre règlement, ou contactez notre service commercial

Cause 1 The HASP dongle is time protected and is about to expire.

Solution

Contact customer support to get a new license.

Cause 2 The computer time (CT) was changed to a date in the future.

Solution

Attention: *Acknowledge the impact of changing the computer time when using a time protected dongle.*

The dongle has a date when it was activated (ACT); the error is produced when the computer time is beyond the activation time plus the delay: $CT > ACT + Delay$.

- If the computer time is changed accidentally to a future date, contact customer support to get a reset code or a new dongle

Advice: *Always check the computer time when moving the dongle to another computer before starting the Advance Design / OMD application; the time has to be synchronized with the real time.*

Error code 304: *The software version is not available for the protection system.*

Displayed message La version du programme n'est pas disponible avec le système de protection en place.

Cause The HASP dongle has a license for an older software version than the one currently installed on the computer (e.g. the user is running software version 3, but on the HASP dongle the license is for version 2).

 **Solution**

Contact customer support to get a license for the new version.

Error code 307: *The protection system has not been initialized.*

Displayed message Le système de protection n'a pas été initialize

Cause The HASP dongle was not initialized with the license code.

 **Solution**

Enter the license code received from customer support.

Error code 308: *The protection system has been altered.*

Displayed message Le système de protection a été altéré

Cause The license code on the HASP dongle has been corrupted.

 **Solution**

Re-enter the license code received from customer support.

Error code 309: *The codes sent by the key are not the right ones. Verify the protection system installation.*

Displayed message Les codes renvoyés par la clé ne sont pas les bons. Vérifiez l'installation du système de protection.

Cause 1 The HASP dongle is not a valid **Advance Design / OMD** dongle.

Solution

Plug in the right **Advance Design / OMD** HASP dongle.

Cause 2 There are several USB HASP dongles and the protection points to a USB port which is not an **Advance Design / OMD** dongle.

Solution

If there are several USB dongles, set the correct port in the “Protection” application to point to a valid **Advance Design / OMD** dongle.

Error code 400: *Protection type is not defined at the general environment level.*

Displayed message Le type de protection n'est pas défini au niveau de l'environnement général

Cause The protection type is not defined in the “Protection” application.

Solution

In the “Protection” application the “Type” is not defined. Choose “HASP” for a local dongle or “NETHASP” for a network dongle.

Error code 451: *To use the software on the protection server it is necessary to select the 'NETHASP' protection type*

Displayed message Pour utiliser le programme sur le serveur de protection, il est nécessaire de choisir le type de protection 'NETHASP'.

Cause If the local dongle is of the “NETHASP” type, the user sets the protection type to “NETHASP (Local)” and wants to run the software.

Solution

To run the software on a computer with “NETHASP” dongle, set the protection type to “NETHASP” instead of “NETHASP (Local)”.

Error code 500: *The license code does not have 21 characters*

Displayed message Le code confidentiel ne comporte pas 21 caractères.

Cause The license code entered in the **Modules** field of the “Protection” component is shorter than 21 characters.

 **Solution**

Re-enter the code or – if the code sent by customer support is shorter than 21 characters – ask for a new code.

Error code 501: *Invalid license code*

Displayed message Le code confidentiel n'est pas valide.

Cause 1 The license code received from customer support is not valid.

 **Solution**

Ask for a new code.

Cause 2 The license code was entered in another field in the “Protection” component.

 **Solution**

Verify that the license code is entered in the **Modules** field of the “Protection” component and not in the **Delay** field (or vice versa).

In case of OMD protection, make sure the EFFEL code is entered in the **Modules** field on the **Effel** protection tab, etc.

Appendix

Bellow are listed the available tools and general documentation from Aladdin Knowledge Systems Ltd.

HASP_LM_setup.zip	HASP Network License Manager - version 8.32.5.40 (May 2008)
HASP_SRM_Runtime_setup.zip	HASP SRM Environment – version 5.50 (July 2008)
MONITOR.ZIP	Aladdin Monitor – version 1.4 (April 2007)
DiagnostiX.zip	Aladdin DiagnostiX – version 1.10 (May 2007)
HASP_SRM_Guide.pdf	HASP SRM Status codes – page 257
HASPMAN.PDF	HASP4 Status codes – page 149